



Table 4 : Testing and Inspection Intervals for Electrical Equipment

CAUTION - This information **must** be read in conjunction with AS/NZS 3760:2010 as a whole, and particularly Clause 2.1

Type of environment and/or equipment (a)	Interval between inspection and tests				
	Equipment including Class I equipment, Class II equipment, cord sets, cord extension sets and EPOD's (b)	Residual Current Devices (RCD's)			
		Push Button test by user		Operating time and push-button test	
		Portable (c)	Fixed (d)	Portable (e)	Fixed (f)
1 Factories, workshops, places of work or repair manufacturing, assembly, maintenance or fabrication	6 months	Daily, or before every use, which ever is the longer	6 months	12 months	12 months
2 Environment where the equipment or supply flexible cord is subject to flexing in normal use OR is open to abuse OR is in a hostile environment	12 months	3 months	6 months	12 months	12 months
3 Environment where the equipment or supply cord is NOT subject to flexing in normal use and is NOT open to abuse and is NOT in a hostile environment	5 years	3 months	6 months	2 years	2 years
4 Residential type areas of hotels, residential institutions, motels, boarding houses, halls, hostels, accomodation houses, and the like	2 years	6 months	6 months	2 years	2 years
5 Equipment used for commercial cleaning	6 months	Daily, or before every use, which ever is the longer	NA	6 months	NA
6 Hire Equipment Inspection Test and Tag	Prior to hire	Including push-button test by hirer prior to hire		NA	NA
	3 months	NA		3 months	12 months
7 Repaired, serviced and second-hand equipment	After repair or service which could affect electrical safety, or on reintroduction to service, refer to AS/NZS 5762				